BUFFALO™

LinkStation 200

User Manual

www.buffalotech.com

35020312-01
2014-01

Contents

Chapter 1 Installation.....7

Diagrams.....7

Turning the LinkStation On and Off 8

Chapter 2 Configuration 9

Opening Settings from a Computer 9

Opening Easy Admin 9

Opening Advanced Settings 12

Opening Settings from a Smartphone 13

iPhone, iPad, and iPod touch 13

Android Smartphones and Tablets.....15

Chapter 3 Remote Access.....17

WebAccess 17

Configuring from a Smartphone 17

Configuring from a Computer 25

FTP.....28

Chapter 4 Access Restrictions.....31

Configuring Access Restrictions on Users and Groups 31

Adding Shared Folders.....31

Adding Users 34

Adding Groups.....37

Access Restrictions....37
Active Directory....39
NT Domains....41
Delegating Authority to an External SMB Server....43

Chapter 5 Managing Storage....46
Adding an External Hard Drive....46
Connect an External Drive....46
Compatibility....46
Dismounting Drives....46
Dismounting with the Function Button....47
Dismounting from Settings....47
Checking Drives....48
Formatting Drives....49
Formatting External Drives....50
Erase Data on the LinkStation Completely....51
Disk Quotas....52
Quotas for Users....52
Quotas for Groups....52

Chapter 6 Backup....54
Back Up from the LinkStation....54
Preparing a Backup Destination....54
Configuring a Backup Job....56
Backing Up Your Mac with Time Machine....58

Copying from a USB Device 62
Configuring Direct Copy 62
Starting Direct Copy 63

Chapter 7 Multimedia 65

DLNA 65
Configuration from Smartphone 65
Configuration from Easy Admin 66
Configuration from Advanced Settings 66
Play Files 68
Connected DLNA-compatible Devices 68
Streaming to DLNA-compatible Devices 69
Disabling Playback from Specific Devices 69
iTunes Server 70
BitTorrent 71
Configuring BitTorrent 71
Opening Download Manager 72
Downloading Files 74
Connecting a Printer 74
Setting up a Printer from a Smartphone 75
Settings up a Printer with Windows 8.1, Windows 8, Windows 7, or Windows Vista 75
Setting Up a Printer with Windows XP 76

Chapter 8 Advanced Features 78

Email Notification 78

Sleep Mode 79
Encrypting Data Transmission 80
Encrypting Settings Data 80
Encrypting FTP Transfer Data 80
SSL Encryption 80
Restoring Factory Defaults.....81
Initializing from Settings 81
Initializing with the Function Button 81
Online Update 81
Name, Date, Time, and Language 82
Jumbo Frames 84
Changing the IP Address 85

Chapter 9 Utilities.....86
NAS Navigator2 for Windows.....86
Mount as Network Drive.....88
Changing the IP Address 89
NAS Navigator2 for Mac OS.....89
Mount as Network Drive.....90
Changing the IP Address 91

Chapter 10 Appendix 93
When the Power LED Blinks.....93
Default Settings 95
Specifications 95

Compliance Information.....96

FCC Statement.....96

Environmental Information 97

Models 97

Chapter 1 Installation

Diagrams

LS210D



1 Power LED
The white power LED will light up while the LinkStation is on.
The white power LED blinks while booting or shutting down.
The red power LED blinks when an error occurs.
If there is a status message, the power LED glows amber.
If there is a new firmware available, the power LED blinks amber.

2 Function LED
This LED glows while the LinkStation is being initialized and while dismounting USB devices.

3 Function Button
Use this button for Direct Copy, dismounting USB devices, and initializing settings.

4 Power Switch

Move the switch up and down to power on and off.

5 USB 2.0 Port
Compatible Buffalo USB hard drives, USB flash drives, digital cameras, USB UPS connection, and USB printers can be connected. USB hubs are not supported.

6 LAN Port
Connect to a router, hub, or switch on your Ethernet network with the included Ethernet cable.

7 Link and Activity LED

This LED shows network activity. It blinks green when the LinkStation is accessed over the network.

8 Power Connector
Use the included power cable to connect to a surge protector or outlet.

9 Anti-Theft Security Slot
Use this slot to secure your LinkStation with a cable lock (not included).

Turning the LinkStation On and Off

Move the power switch on the back of the LinkStation to the "on" position to turn it on. To turn it off, move the switch to the "off" position and wait for the unit to fully shut down before unplugging it. Never unplug the AC adapter without properly shutting down the LinkStation first.

When all the LEDs on the front of the LinkStation turn off, the shutdown process is complete.

Chapter 2 Configuration

Configure and administer your LinkStation using the Settings interface, accessible from a browser window. Open the interface using the procedure below or type the LinkStation's IP address in the URL field of your browser. Within Settings, the Easy Admin page gives you quick access to commonly used settings.

Opening Settings from a Computer

Note: Internet Explorer 9, Firefox 18, Google Chrome 24, Safari 5, and later are supported. If you have difficulty viewing Settings, check the following:

- If you have a proxy server enabled in the browser settings, disable the proxy server.
- With Internet Explorer, set security to *Local intranet*. On Windows Server 2012 or Windows Server 2008, higher-level security is configured by default. Set the security to a lower level temporarily.

Opening Easy Admin

The Easy Admin page makes it easy to change common settings. Follow the steps below to open Easy Admin.

1 Open NAS Navigator2 by double-clicking the icon.

2 Right-click on your LinkStation's icon and choose *Settings*. For Mac OS, click your LinkStation's icon while holding down the control key, then select *Settings*.



3 The Easy Admin screen will open.



Notes:

- If you click any buttons, you will need to enter a username and password.



- Username/Password Combinations:

Username	Password	Settings Available
admin	password	All
guest	blank	LinkStation's name, IP address, workgroup, drive status, firmware version
your username	your password	LinkStation's name, IP address, workgroup, drive status, firmware version, and your password.

- If the time-out period is set to "10 minutes", you will be logged out of Settings after 10 minutes of inactivity. You will also be logged out when you reboot the LinkStation or close the web browser, even if you select "Unlimited".
- Click *Secure Connection* to log in with an encrypted connection.
- You can also use Bonjour to log in to Settings from Mac OS. In Safari, click *View - Show Bookmarks Bar*. From Bookmarks, click *Bonjour - LinkStation name*.

Getting Started

The wizard lets you configure the following settings:

- Changing administrator password
- Creating shared folders
- Access restrictions



The first time you access your LinkStation, this page will open. Step through the wizard to change your administrative password and configure time settings.


BUFFALO
admin
Language
English
Getting Started > Change Administrator Password
Change the administrator password.
For security, please choose a new administrator password below.
Show entered password
Password:
Confirm Password:
The password may include up to 20 alphanumeric characters, hyphens (-), underscores (_), periods (.), and symbols !, #, &, @, $, *, ^, %.
Back
Next

WebAccess

Configure WebAccess to access your LinkStation remotely. Refer to "WebAccess" for more information.



BitTorrent

Configure BitTorrent to download large files efficiently. Refer to "BitTorrent" for more information.



DLNA

Configure DLNA to stream media files to DLNA-compatible devices on the LAN. Refer to "DLNA" for more information.

Opening Advanced Settings

1 Click *Advanced Settings* in Easy Admin.



2 Enter the administrator username and password, then click *OK*.



3 The Advanced Settings screen will open.



Note: To go back to Easy Admin, click the Home icon.

Opening Settings from a Smartphone

You can access your LinkStation's Settings from your iOS or Android device. Download and install "SmartPhone Navigator" from the App Store or Google Play.

Notes:

- If you have an older version of SmartPhone Navigator installed on your phone, update it to the latest version. Your icons and software may be slightly different from the examples in this manual.
- You must be logged in as an administrator to change settings. To use SmartPhone Navigator, log in as a member of the administrators group.

iPhone, iPad, and iPod touch

1 Open "SP Navigator" on your iOS device.

2 Tap *Open Settings*.



3 Settings will be displayed.



Notes:

- The first time you go through setup, you'll be given a chance to change the default password and correct the time zone settings. Step though the wizard to change these settings.
- If you tap any buttons, you will need to enter a username and password.

- Tap *Desktop* to show Advanced Settings. This screen gives the full array of settings that could be changed from a computer, but is not optimized for smartphones.

Android Smartphones and Tablets

1 Open SmartPhone Navigator" on your Android device.



2 Tap *Open Settings*.



3 Settings will be displayed.



Notes:

- The first time you go through setup, you'll be given a chance to change the default password and correct the time zone settings. Step though the wizard to change these settings.
- If you tap any buttons, you will need to enter a username and password.

- Tap *Desktop* to show Advanced Settings. This screen gives the full array of settings that could be changed from a computer, but is not optimized for smartphones.

What the Mobile Mode Settings Can Do

You can change the following settings from your mobile device:

- Create users, change usernames and passwords.
- Create shared folders.
- Configure WebAccess settings to remotely access your LinkStation.
- Configure your LinkStation to use with DLNA-compatible devices on the LAN.
- Configure and dismount USB devices connected to your NAS, including Direct Copy options and print server settings.

Chapter 3 Remote Access

WebAccess

WebAccess is a program for accessing the files in the shared folder of your LinkStation from your computer, smartphone, or tablet through the Internet.

Notes:

- Be careful when configuring WebAccess. Certain settings can make the files in the shared folder available to anyone on the Internet, without any access restrictions.

Configuring from a Smartphone

iPhone, iPad, and iPod touch

Notes:

- Download the "SmartPhone Navigator" and "WebAccess" applications from the App Store.
- You can also configure WebAccess settings from the mobile mode Settings.

1 Open "SP Navigator" on your iOS devices.

2 Tap *NAS Setup*.



3 Enter a username and password. This will create a new user. Tap *Next*.



4 Enter the password from the previous step again and tap *Next*.



5 Tap *OK*.

Note: If UPnP is not enabled on your network, you will only be able to access your NAS from the local network. To

use WebAccess from outside your home, either enable UPnP in the router or open port 9000 for WebAccess in your router's settings.


Confirm
WebAccess is configured for local network use only. To use WebAccess from outside the local network, either enable UPnP in the router, or open port 9000 in your router's settings.
OK

6 Enter the BuffaloNAS.com name and tap *Set*.


Back
NAS Setup
Choose a BuffaloNAS.com name. This name will be used to access the shared folder with WebAccess. The BuffaloNAS.com name may contain up to 20 alphanumeric characters.
sampleuser
Cancel
Set

7 Tap *Browse*.

8 WebAcces will launch.
Tap *OK* if the following message is displayed.



9 Tap your NAS's hostname to open the shared folder.

Note: For more details, select *View Manual* from the application. For additional features, install the WebAccess

application on your smartphone.

Android Smartphones ad Tables

Notes:

- Download the "SmartPhone Navigator" and "WebAccess" applications from the Google Play.
- You can also configure WebAccess settings from the mobile mode Settings.

1 Open "SmartPhone Navigator" on your Android devices.



2 Tap *NAS Setup*.



3 Enter a username and password to create a user for WebAccess and tap *Next*.



4 Tap *OK*.

Note: If UPnP is not enabled on your network, you will only be able to access your NAS from the local network. To use WebAccess from outside your home, either enable UPnP in the router or open port 9000 for WebAccess in your router's settings.

Confirm
WebAccess is configured for local network use only. To use WebAccess from outside the local network, either enable UPnP in the router, or open port 9000 in your router's settings.
OK

5 Enter the BuffaloNAS.com name and tap *Set*.


Set BuffaloNAS.com Name
Choose your BuffaloNAS.com name. You will use this name for opening the shared folder with WebAccess. The BuffaloNAS.com name may contain up to 20 alphanumeric characters.
sampleuser001
Cancel
Set

6 Tap *Browse*.



7 WebAcces application will launch.
Tap *Close* if the following message is displayed.



8 Tap *NAS List*.



You may now access the shared folder on the LinkStation.

Note: For more information, select *View Manual* from the application. For additional features, install WebAccess application on your smartphone.

If Creating BuffaloNAS.com Name Failed

If UPnP is disabled in your router, creating the BuffaloNAS.com name from SmartPhone Navigator may fail. If this happens, try the following procedure.

1 Tap the "SmartPhone Navigator" icon on your smartphone.

2 Tap *Open Settings*.

3 Tap *WebAccess*.



4 Select the access level from the drop-down list and tap *Apply*.

5 Tap *OK*.

6 Enter the desired BuffaloNAS.com name.

7 Select "Configure router's port settings manually", enter the router's port number, and tap *Apply*.

Configuring from a Computer

Configuration from Easy Admin

Note: Use compatibility mode to use WebAccess with Internet Explorer on Windows 8 and Windows 8.1.

1 Click *WebAccess* in Easy Admin.



2 Move the WebAccess switch to the On position to enable WebAccess.


WebAccess
On
WebAccess allows you to create a secure personal cloud for easy remote access and file sharing with anyone, anywhere over the Internet while your data remains securely stored in one place on your home network.

3 Select the level of access for each shared folder from the drop-down list.



4 Enter a BuffaloNAS.com name for your BuffaloNAS account.



Note: The BuffaloNAS.com name may contain between 3 to 20 alphanumeric characters, underscores (_), and hyphens (-). The BuffaloNAS.com name is case-sensitive.

5 Click *Apply*.

6 Continue with the procedure at http://buffalonas.com/manual/setup/en/.

Configuration from Advanced Settings

Note: Use compatibility mode to use WebAccess with Internet Explorer on Windows 8 and Windows 8.1.

1 Navigate to *File Sharing* - *WebAccess*. Click to the right of "WebAccess".

2 Click *Edit*.



3 Configure the desired settings, then click *OK*.



- To use SSL encryption for more secure data transfers, enable "HTTPS/SSL Encryption".
- Some WebAccess applications may not support HTTPS/SSL encryption. Disable it if this is an issue. For more details, refer to the WebAccess Help Guide.
- You may use the default BuffaloNAS.com registration, or disable to use a different DNS server.
- Choose a "BuffaloNAS.com name" and "BuffaloNAS.com key" for your WebAccess account. Names and keys may use 3 to 20 alphanumeric characters, underscores (_), and hyphens (-).
- If "Exclusive Session" is enabled, users cannot log multiple computers in to WebAccess. Only the last login will be active.
- Enter a time in minutes (1 to 120 or "Unlimited") before inactive users are logged out of WebAccess.

4 Click *OK*.

5 Move the switch to the

position to enable WebAccess.

6 Click to the right of "Folder Setup".

7 Select a shared folder to publish.

Notes:

- For best results, create a new dedicated share for WebAccess.
- When accessing shared folders through WebAccess from a remote location, the username and password may be required for certain operations. For best results, create a user account with permissions on the WebAccess share before using WebAccess.

8 Click *Edit*.

9 Navigate to *File Sharing - Folder Setup* and choose the folder you will use for WebAccess. Enable "WebAccess LAN protocol support".



Notes:

- The following levels of security are available:
  "Allow Anonymous" - Anyone can access (view) shared folders.
  "Allow All Groups and Users" - All groups and users registered on the LinkStation or TeraStation can use WebAccess.
  "Use Inherited Folder Permissions" - Users and groups have the same access permissions with WebAccess that they do locally. If access restrictions are not set for the shared folder, then this option will not be shown.
- When a user or group can access a folder through WebAccess depends on a combination of WebAccess settings and the shared folder's settings.

Folder Setup	WebAccess Public Mode	Allow Anonymous		Allow All Groups and Users		Use Inherited Folder Permissions	
	Folder Attribute	Read & Write	Read Only	Read & Write	Read Only	Read & Write	Read Only

WebAccess Account	Not logged in	R	R	-	-	-	-
	User with read & write access	R/W	R	R/W	R	R/W	R
	User with read-only access	R/W	R	R/W	R	R	R
	Group with read & write access	R/W	R	R/W	R	R/W	R
	Group with read-only access	R/W	R	R/W	R	R	R
	Other users	R/W	R	R/W	R	-	-

R: Read only, R/W: Read and write, -: No access

10 Continue with the procedure at http://buffalonas.com/manual/setup/en/.

Note: If you change your BuffaloNAS.com name after WebAccess has been configured, WebAccess may no longer work properly. If this happens, disable and then re-enable WebAccess.

FTP

By default, the LinkStation's shares are only accessible by users connected to the same network or router as the LinkStation. The optional FTP server allows users outside the local network to access the LinkStation.

Note: FTP is intended for users who already have FTP client software and have experience with it.

1 In Advanced Settings, navigate to *File Sharing - Folder Setup*. Move the FTP switch to the On position to enable FTP.

2 Click to the right of "Folder Setup".

3 Choose a folder to enable remote FTP access on.

4 Click *Edit*.

5 Select read-only or read & write for the shared folder's attribute, check "FTP" under "LAN Protocol Support", and click *OK*.



Accessing the LinkStation with an FTP client

- To access the LinkStation via FTP, configure your FTP client software with the following settings:
  Hostname: IP address of the LinkStation
  Username: The LinkStation's username
  Password: The LinkStation's password
  Port: 21
- Shared folders connected by FTP are available from the "/mnt" directory. The default locations are:
  /mnt/disk1/share
  /mnt/usbdisk1

Accessing the LinkStation with an anonymous user:

- To allow anonymous access to your FTP share, disable access restrictions.
- To access the LinkStation via anonymous FTP, configure your FTP client software with the following settings:
  Hostname: IP address of the LinkStation
  Username: Anonymous
  Password: Any character string
  Port: 21

  Notes:
  - If the LinkStation joins a domain, anonymous users cannot access it.
  - Don't use FTP to share files and folders with multi-byte characters in their names with a Mac. Use an AFP or SMB

connection instead.

- If a file was created or copied by AFP, you may not be able to delete it using an FTP connection. If this occurs, use an SMB or AFP connection instead to delete the file.
- For FTP connections, make sure that the total filename including directory path is 250 single-byte characters or less.

Chapter 4 Access Restrictions

You may restrict access to specific shared folders, including external USB drives.

Notes:

- Access restrictions can be set separately for each shared folder, but not for subfolders within the shared folders.
- Configure access restrictions through Settings. Configuring access restrictions through Windows is not supported and may cause unexpected behavior.

Configuring Access Restrictions on Users and Groups

Adding Shared Folders

Configuration from a Smartphone

1 In the mobile mode Settings, tap *Folder Setup*.



2 Tap *Create Folder*.



3 Enter a folder name and description and tap *Apply*.



Note: Folder names may contain up to 27 alphanumeric characters and symbols. The description may contain up to 75 alphanumeric characters.

Configuration from a Computer

1 In Advanced Settings, navigate to *File Sharing - Folder Setup* and click the icon.

2 Click *Create Folder*.

3 Configure the settings, then click *OK*.



Notes:

- Names may contain up to 27 alphanumeric characters, hyphens (-), and underscores (_). Do not use a symbol as the first character in a name.
- The description may contain up to 75 alphanumeric characters, hyphens (-), underscores (_), and spaces. Do not use a symbol or space as the first character.
- You may create up to 400 shared folders.
- The names of shared folders should not use characters from more than one language. For example, mixing Japanese and Korean characters in names is not supported.
- If multi-byte characters are used in shared folder names, configure the client language to match the characters in *Management - Name/Time/Language*.

Recycle Bin

To protect your data from accidental deletion, you may configure your LinkStation to use a recycle bin instead of deleting files immediately. The recycle bin will only work with SMB connections.

Accounts

Your LinkStation's username and password should be the same as your Windows username and password. If they are different, you may not be able to access folders on the LinkStation with access restrictions configured.

Read-only Shares

By default, new shares are set with read & write access, but you may change the attribute to "Read-only" in "Shared Folder Attributes". Read-only shares and HFS+ formatted USB hard drives will have "Read-only" added to the shared folder description.

Hidden Shares

To hide a shared SMB folder, select "Hidden Share (SMB Only)" and click *OK*. To open a hidden folder, click *Start - Search programs and files* and enter "\\LinkStation's name\Shared folder names$\" for the name. Example: If the LinkStation's name and shared folder name is "LSXXX001" and "share", you should enter "\\LSXXX001\share$\" in the search box.

Note: AFP or FTP folders cannot be hidden.

Adding Users

Configuration from a Smartphone

1 In the mobile mode Settings, tap *Users*.



2 Tap *Create User*.



3 Enter the desired username, password, and description, and tap *Apply*.

Note: Usernames may contain up to 128 alphanumeric characters and symbols. Passwords may contain up to 20 alphanumeric characters and symbols.

Configuration from a Computer

1 In "File Sharing", click the icon to the right of "Users".

2 Click *Create User*.

3 Enter the desired settings, then click *OK*.



Notes:

- Usernames may contain up to 128 characters, including hyphens (-), underscores (_), periods (.), !, #, &, @, $, *, ^, and %. Do not use a symbol as the first character.
- For Windows 8 and Windows 8.1, use a local username instead of your Windows Live ID.
- The user ID should be a number from 1000 to 1999. Each user ID should be unique. If this field is left blank, a user ID is assigned automatically.
- When you log in to Settings as a registered user, you can see the LinkStation's name, IP address, workgroup, and disk status, and modify the password.
- Do not duplicate user IDs, group IDs, usernames, or group names. Each should be distinct and unique.
- The description may contain up to 75 alphanumeric characters, hyphens (-), underscores (_), and spaces. Do not use a symbol or space as the first character.
- When setting users with access privileges, a maximum of 300 users, including "admin" and "guest", can be registered in the LinkStation.
- Passwords may contain up to 20 alphanumeric characters and the following characters: - _ @ ! # $ % & ' ( ) * + , . / ; < > = ? " [ ] ^ { } | ~. Do not use a symbol other than an underscore (_) as the first character.
- Use the same username and password for both Windows and the LinkStation or you may not be able to access shared folders.
- If a user belongs to multiple groups, the most strict access restrictions will apply. For example, if a user is added to a group with read and write access, and also to a read-only group, the user will effectively have read-only access.

Shared Folder Owners

To confirm the owner of a shared folder from Windows XP, from the *Properties* screen of the file or folder, open a new window from the *Security* tab. Click *Advanced*, then click the *Owner* tab.

Adding Groups

1 In "File Sharing", click the icon to the right of "Groups".



2 Click *Add Group*.

3 Enter settings, then click *OK*.



Notes:

- Group names may contain up to 20 alphanumeric characters, hyphens (-), underscores (_), and periods (.). Do not use a symbol other than an underscore (_) as the first character.
- Group descriptions may contain up to 75 alphanumeric characters, hyphens (-), underscores (_), and spaces. Do not use a symbol or space as the first character.
- If the group ID field is left blank, a group ID is automatically assigned. Use numbers between 1000 and 1999 to set a group ID manually. Don't use duplicate group IDs.
- You may register up to 300 groups with the LinkStation.
- If you are logged in as a member of the general users group, you can only change your own password. If you're logged in as an administrator, you can change any settings, including other users' passwords. If you are logged in as a member of the power users group, you can create and edit shared folders, users, and groups.

Access Restrictions

1 In "File Sharing", click the icon to the right of "Folder Setup".

2 Click the shared folder that you want to set access restrictions for.



3 Click *Edit*.

4 Enable "Access Restrictions".

5 Select the level of access for the user or group you added.

: Read and write access allowed : Read access allowed : Access prohibited



Notes:

- An example of access restrictions by user is shown in the screen. To apply access restrictions by group, click the *Local Groups* tab and select group permissions.
- If both read-only and read & write permissions are given to a user, the user will have read-only access.

6 Click *OK*.

Notes

- The following characters are handled differently by Mac OS and Windows. Avoid using these characters when sharing data between Mac OS and Windows:

  — ~ ¥ ¥ – ¢ £ ¬

- Windows does not support some characters that Mac OS and the LinkStation allow. If you create a filename on a Mac with any of the following characters, it will not display correctly on a Windows computer and you may have to connect to the LinkStation via AFP in order to display or copy any of the following characters on a Mac computer.

  ? [ ] / \ = + < > ; : " , | *

- Do not use any of the following words as a username or group name: root, bin, daemon, sys, adm, tty, disk, lp, sync,

shutdown, halt, operator, nobody, mail, news, uucp, ftp, kmem, utmp, shadow, users, nogroup, all, none, hdusers, admin, guest, man, www, sshd, administrator, ftpuser, apache, mysql

- Do not use any of the following words as the name of a shared folder. These words are reserved for internal use by the LinkStation: info, spool, lost+found, global, printers, homes, lp, authtest, ram, msdfs_root, mt-daapd, usbdisk# (where # is a number, for example: usbdisk1)
- Don't use the following unsupported characters in shared folder names, workgroup names, or filenames:

- File and folder names may contain up to 255 single-byte characters.
- Configure hidden and read-only file attributes in Settings. Configuring them from within Windows is not supported and may cause unexpected behavior.
- Folder and workgroup names whose names contain non-Roman characters may not be displayed correctly.
- If shared folders are accessed from a Macintosh, information files for the Macintosh may be generated automatically. Do not delete these files. If they are deleted using Windows, this may prevent further access from a Macintosh.
- If an SMB connection is used with OS X 10.3.9, the names of mounted volumes may appear as unreadable characters in Finder and other applications. This is not a problem with the filename or data.
- The LinkStation belongs to the default zone in AppleShareServer; the zone cannot be specified.
- When files are copied to the LinkStation or to a USB drive connected to the LinkStation, file information such as date created, date modified, and other date information may be updated or changed.
- Hard drive capacity is shown in Settings in actual gigabytes. The Properties window in Windows may show GiB instead, which will be a smaller number.
- During a file transfer, if settings are changed, the file transfer operation may be aborted.
- File copying to the LinkStation is protected by a journaling file system. If the Ethernet cable is disconnected or a power outage occurs while copying data, the following may occur:

  - Preset data such as the LinkStation name, users, and groups may be erased.

  - An incomplete file may be copied and the file can no longer be deleted. If this happens, restart the LinkStation, delete the file, and perform the copy operation again.
- After a drive is formatted, the "% Used" and "Amount Used" in Settings will not be 0. This is because some drive space is used for the system area.

Active Directory

The LinkStation can join an Active Directory domain. Up to 1000 domain users and 1000 groups may be downloaded from Active Directory.

Note: If usernames or group names from Active Directory include multi-byte characters, you will not be able to configure access restrictions for them.

1 In Advanced Settings, select *Network*.



2 Click to the right of "Workgroup/Domain".

3 Click *Edit*.

4 Select "Active Directory" and click *Next*.

5 Click *Yes*.

6 Enter the desired settings, then click *OK*.



7 Choose *Folder Setup*.

8 Click a shared folder that you want to set access restrictions for.



9 Click *Edit*.

10 Enable "Access Restrictions".

11 Select the level of access for the user or group:
: Read and write access allowed : Read access allowed : Access prohibited

12 Click *OK*.

Notes:

- If both read-only and read & write permissions are given, the user will have read-only access. The most restrictive access setting will apply.
- To have the LinkStation join an Active Directory domain, configure it to use a DNS server that can resolve names for the Active Directory domain.
- After building an Active Directory domain, the administrator password for joining the domain must be changed at least once, or joining the Active Directory domain will fail.
- The DNS name and NetBIOS name of Active Directory domains should be identical.
- If there are more than 5 minutes difference between the LinkStation's clock and the domain controller's clock, joining the domain or authenticating domain users and groups may fail. For best results, use an NTP server to set the time for all network devices.
- The LinkStation supports a domain environment with a maximum of 1000 users and 1000 groups. 10,000 users and 10,000 groups can be downloaded from the domain controller but are not supported.
- To use the LinkStation as a member server in an Active Directory domain, the LinkStation should be logged in to the domain and accessed from a computer that is not a member of the domain with a valid domain account.
- If the LinkStation is a member server of an Active Directory domain, you cannot connect as a guest user via AFP.
- If your LinkStation is a member server in an Active Directory domain and you change the authentication method to "Workgroup", the account on the domain controller will not be deleted automatically.
- When the LinkStation joins an Active Directory domain, FTP is disabled. Before use FTP, move the FTP switch back to the

position.
- Don't disable the SMB protocol while Active Directory is used for access restrictions. If you do, you will need to enable SMB again and reconfigure AD from scratch.

NT Domains

In an NT domain environment, the LinkStation uses account information from the NT domain server to set access restrictions for files and folders on the LinkStation. There's no need to perform individual account management for the LinkStation. If multiple LinkStations are installed on the network, the account information is centrally managed in the NT domain, greatly reducing the operations required for installation and management.

Note: A maximum of 1000 domain users and 1000 groups can be downloaded from an NT domain server.

1 Create an account on the domain controller for the LinkStation.

2 In Advanced Settings, click *Network*.



3 Select *Workgroup/Domain*.

4 Click *Edit*.

5 Select "NT Domain", then click *Next*.

Note: To use Active Directory from Windows 2000 or Windows Server 2003, select "Active Directory" instead of "NT Domain".

6 Click *Yes*.

7 Enter settings and click *OK*.



8 Click to the right of "Folder Setup".



9 Click a shared folder for which you want to set access restrictions.



10 Click *Edit*.

11 Enable "Access Restrictions".

12 Select the level of access for "Domain Users" or "Domain Groups" you added.
: Read and write access allowed : Read access allowed : Access prohibited

13 Click *OK*.

Notes:

- If you change the LinkStation's name, you will no longer be able to use domain users and groups or access restrictions. To repair this, rejoin the domain.
- If both read-only and read & write permissions are given to a user, the user will have read-only access. The most restrictive attribute will apply.
- If a domain username is more than 20 bytes long, the LinkStation truncates it to 20 bytes.
- The LinkStation supports a domain environment with a maximum of 1000 users and 1000 groups. 10,000 users and 10,000 groups can be downloaded from the domain controller but are not supported.
- To use the LinkStation as a member server in an NT domain, the LinkStation should be logged in to the domain and accessed from a computer that is not a member of the domain with a valid domain account.
- If the LinkStation is a member server of an NT domain, you cannot connect as a guest user via AFP.
- When you change the user or group settings on the domain controller, these changes may not take effect immediately on the LinkStation until it is rebooted.
- If your LinkStation is a member server in an NT domain and you change the authentication method to "Workgroup", the account on the domain controller will not be deleted automatically.
- If the LinkStation has joined a domain network, you cannot connect to it via FTP.
- Don't disable the SMB protocol while an NT domain server is used for access restrictions. If you do, you will need to enable SMB again and reconfigure the NT domain settings from scratch.

Delegating Authority to an External SMB Server

LinkStations on your network can be linked to an authentication server for centralized management of user accounts and passwords. The authenticationserver should be a TeraStation or another LinkStation.

Notes:

- Other external SMB servers are not supported. Use a TeraStation or a LinkStation for the authentication server.
- When saving changes to the external authentication server settings, click *Yes* to convert all local users to external authentication users. If external authentication is disabled, local user passwords will need to be reconfigured.
- Make sure that SMB2 is disabled before using external authorization with Windows 8 and Windows 8.1.
- Using external authentication may require the default security settings in Windows to be changed. An easy way to do this is to run the File Sharing Security Level Change Tool, available from www.buffalotech.com. This simple tool will let you change or restore your Windows security settings to work with external authentication.

1 In Advanced Settings, click *Network*.



2 Choose *Workgroup/Domain*.



3 Click *Edit*.

4 Select "Workgroup".

5 Click *Next*.

6 Enter a workgroup name. Select "Assign authorization to external SMB server" and enter the authentication server's IP address (recommended) or name. Check "Automatic user registration" and "Use shared folder for authorization testing". Enter the name for authorization testing and click *OK*.



7 A shared folder for authentication has been created on the LinkStation. Users registered to the specified authentication server are automatically registered as users on the LinkStation when they open the shared folder for authentication. You can also register users directly. Connect to the authentication folder via SMB, not FTP or AFP.

8 Choose *Folder Setup*.

9 Choose a shared folder to set access restrictions on.



10 Click *Edit*.

11 Enable "Access Restrictions".

12 Select the level of access:
: Read and write access allowed : Read access allowed : Access prohibited

13 Click *OK*.

Notes:

- If both read-only and read & write permissions are given to a user, the user will have read-only access. The most restrictive attribute will apply.
- If access restrictions are set for users and groups registered in the authentication server, guest or anonymous connection is not possible with AFP or FTP connections.
- Users who are automatically registered belong to the "hdusers" group. They can be added to other groups from within group settings.
- The names of registered users are listed in "Users" - "External Users". To delete a user who was registered automatically, select that user and click *Delete External User*.
- When connecting through AFP or FTP, always use an IP address. Using a server name may cause problems with authentication.
- To specify a server from another subnet, enter its IP address.
- Use AFP to access access-limited shared folders from OS X 10.7 instead of SMB. Enable "AFP (Mac)" under "LAN Protocol Support" on the destination folders to use AFP.
- Use OS X 10.5 or later with external authentication. Earlier versions of OS X aren't supported.

Chapter 5 Managing Storage

Adding an External Hard Drive

Connect an External Drive

Your LinkStation includes a USB port and you can connect an external drive to this port. It will appear as a shared folder on the LinkStation. Formatted drives are detected automatically. Unformatted drives should be formatted in Settings.

After a USB drive is recognized, Windows adds "usbdisk X" under the LinkStation in "Network", where "X" is the USB port where the hard drive is connected.

Notes:

- Hubs are not supported. Connect a single USB drive to the USB port.
- Backup data from Mac OS may include characters that cannot be written to FAT16 or FAT32 drives such as ".DS_Store". For best results, reformat the drive before using it as a backup target.

Compatibility

The following devices are supported by the LinkStation:

- USB storage devices
- Card readers (except for card readers that can recognize two or more memory cards)
- Digital cameras
- USB printers

Buffalo external USB drives are recommended.

These devices are not supported:

- DUB and DIU series drives
- Hubs, mice, and keyboards

Connect only one device to a USB port. Some external drives with automatic power-on don't turn on automatically when connected to the LinkStation. Use their manual switch to turn them on. Be sure to connect only one bus-powered drive at a time. If there is insufficient bus power for your USB drive, connect its AC adapter. Note that only the first partition of a connected USB hard drive is mounted. Additional partitions are not recognized.

Note: Hard drives formatted with NTFS, exFAT, or HFS+ will have read-only access.

Dismounting Drives

If the LinkStation is powered on, dismount external drives before unplugging them. You may dismount external drives with the function button, or any drives from Settings. If the LinkStation is off, then all drives are already dismounted and may be unplugged safely.

Note: If you unplug your external drives without dismounting them, Settings may still show "usbdisk" in *File Sharing*

- *Folder Setup*. Reboot your LinkStation to clear it.

Dismounting with the Function Button

If the LinkStation is on, hold down the function button for 3 seconds. The white LED will go out as all attached USB drives are dismounted. You may now unplug them safely.

Dismounting from Settings

Procedure on Smartphones

1 In the mobile mode Settings, tap *USB Device*.

2 Tap *Dismount*.



3 When the completion message is displayed, unplug the USB device and tap *OK*.

Procedure on Computers

1 In Advanced Settings, click *Drives*.



2 Click the icon to the right of "USB Drives".

3 Select the drive to dismount and click *Dismount Disk*. The "Confirm Operation" screen will open. Enter the displayed number and click *OK*.



4 When the following message is displayed, it is safe to unplug the drive.



Note: To remount the drive, unplug it and then plug it back again.

Checking Drives

A disk check tests the data on a drive in the LinkStation or connected via USB for integrity. Errors are fixed automatically. With large drives, a disk check may run for many hours. Shared folders cannot be accessed during a disk check. Do not turn off the LinkStation until the disk check is finished. Use the procedure below to run a disk check.

1 In Advanced Settings, click *Drives*.



2 Select *Drives* to check an internal drive or *USB Drives* to check an external drive.

3 Select the drive to test and click *Check Disk*.



4 Click *Check*. You have the option of deleting information files from Mac OS during the check if desired.


Check Disk
Check Target: Disk 2
Delete Mac OS specific files
Warning: Before running the disk check, check that the disk is not set as a backup device. Do not run the disk check if the disk is set as a backup device.
Check
Cancel

Formatting Drives

Note: Under some circumstances, data deleted when a drive is formatted can be recovered. To ensure that data is "gone forever", a format might not be sufficient. See "Erase Data on the LinkStation Completely".

1 In Advanced Settings, click *Drives*.



2 Select *Drives* to format an internal drive or *USB Drives* to format an external drive.



3 Select the drive to format, then click *Format Disk*.



4 Select a format type and click *Format*.


Format Disk
Format : Disk 2
Format Type:
XFS
GPT Partition
Warning: Before formatting, check that the disk is not set as a backup device. Do not format if the disk is set as a backup device.
Format
Cancel

5 The "Confirm Operation" screen will open. Enter the displayed number and click *OK*.


Confirm Operation
Disk Format
A format will erase all data stored on the target drive or array. During a format, you will not be able to change the LinkStation's settings. To continue, enter the confirmation number displayed below and click 'OK'.
Warning: This operation cannot be canceled.
6 3 8 2
Confirmation Number:
OK
Cancel

6 Depending on the size of your drive, the format may take several minutes to several hours to complete. The power LED will flash during the format. Shared folders cannot be accessed during a format. Do not turn off the LinkStation until the disk format is finished.

Formatting External Drives

Formatted drives are detected automatically. If a drive is not formatted, format it from Settings. Refer to "Formatting Drives" for the procedure.


Format Disk
Format : USB Disk 1
Format Type:
EXT3
GPT Partition
Warning: Before formatting, check that the disk is not set as a backup device. Do not format if the disk is set as a backup device.
Format
Cancel

Notes:

- Do not turn off or disconnect power to the LinkStation while formatting a hard drive.
- For drives of 2.2 TB or larger, make sure that the "GPT Partition" checkbox is selected. If you accidently format a larger drive without GPT, disconnect and then reconnect it before reformatting with GPT.

- The following format types are supported: FAT32 (recommended for connecting to computers), EXT3 (recommended for sharing with other LinkStations), XFS (recommended for adding additional external storage to a LinkStation).

Erase Data on the LinkStation Completely

Under some circumstances, data from formatted drives can be recovered. The disk erasure process in this section does a much more thorough job of erasing data. This procedure is recommended for removing all data from a drive in a way that makes it nearly impossible to recover with current tools. All data on the drives is completely erased. The LinkStation will then be in the following state:

- An empty shared folder on each erased drive
- All settings returned to their default values
- All logs deleted

1 In Advanced Settings, click *Management*.



2 Select *Restore/Erase*.

3 Click *Erase LinkStation*.


Erase
This will erase all data and settings and return the LinkStation to its factory defaults.
Erased data cannot be restored. Several hours will be required for this process.
Erase LinkStation

4 The "Confirm Operation" screen will open. Enter the displayed number, then click *OK*.


Confirm Operation
Format Disk
This action will erase all data on the disk and restore configuration settings to factory defaults.
Warning: This operation cannot be canceled.
6 9 0 3
Confirmation Number:
OK
Cancel

5 All data on the LinkStation will be permanently erased.

Disk Quotas

Notes:

- When using quotas, disable the recycle bin or empty the trash folder often. The limited space includes the space used for trash.
- Quotas apply per drive or per array. If a quota is set to 1 GB, each array or drive can use a maximum of 1 GB.
- Quotas cannot be set for external drives connected to the LinkStation.
- If both user and group quotas are configured for a user, the most restrictive quota will always apply.

Quotas for Users

Follow this procedure to limit the shared folder disk space available for a user.

1 In Advanced Settings, click to the right of "Users".

2 Select the user whose space will be limited.

3 Enable quotas, choose the maximum space the user will be allowed to use, and click *OK*.



Note: If you change the primary group, restart the LinkStation to apply the quota settings.

4 Click *Close*.

5 Click the icon and select *Restart* to apply the quota settings.

Quotas for Groups

Follow the procedure below to limit the space for shared folders that each group can use.

1 In Advanced Settings, click to the right of "Groups".

2 Select the group whose space will be limited.

3 Enable quotas, choose the maximum space the group is allowed, and click *OK*.



4 Click *Close*.

5 In Advanced Settings, click to the right of "Users".

6 Change the user's primary group to the group with the quota, then click *OK*.

7 Click *Close*.

8 Click the icon and select *Restart* to apply the quota settings.

Chapter 6 Backup

Back Up from the LinkStation

You can back up LinkStation folders to:

- A different folder on the LinkStation
- Another LinkStation on the network
- Another TeraStation on the network

Preparing a Backup Destination

First, configure a folder as a backup destination.

1 In Advanced Settings, navigate to *Folder Setup*.

2 Choose the folder to set as a backup destination.

3 Click *Edit*.

4 Under "LAN Protocol Support", check "Backup", then click *OK*.



Note: To configure a password, enter it in the "Remote Backup Password" field. Leave this field blank if you don't want a password. If the target device is configured with a backup password, you can easily find the backup target folder during configuration of the backup job by searching for the password.

Backing up to a LinkStation or TeraStation on another network when connected by a VPN

You can back up to a LinkStation or TeraStation on another network as long as the two networks are connected by a VPN. Follow this procedure to enter the IP address or hostname of the target LinkStation or TeraStation.

1 In Advanced Settings, click *Backup*.



2 Click ⧉ to the right of "Backup".

3 Click *List of LinkStations and TeraStations*.



4 Select the IP address of the LinkStation or TeraStation that you want to set as the backup target. Click *Add*, enter the IP address of the target LinkStation or TeraStation, and click *Close*.



If your setup meets the requirements below, you don't have to configure these settings.

- The source and target LinkStations are on the same network.
- No backup password is set for the target LinkStation.
- No LinkStation from outside the subnet, or connected by a VPN, is used.

Notes:

- To back up data between LinkStations or TeraStations on a network using jumbo frames, make sure that both devices are configured to use identical (or similar) Ethernet frame sizes. If Ethernet frame sizes are significantly different, the backup job may not be properly performed. In such a case, select the default frame size (1518 bytes).
- You can also specify hostname by a fully qualified domain name (FQDN).

Configuring a Backup Job

1 In Advanced Settings, click *Backup*.



2 Click ⧉ to the right of "Backup".

3 Click *Create New Job*.



Note: Up to 8 backup jobs can be configured.

4 Select backup settings such as date and time to run.



Note: The following types of backup jobs may be selected:

Type	Files Included
Normal backup	All files in the source will be backed up to the destination.
Overwrite (incremental)	The first time the backup job runs like a normal backup. In subsequent backups, files added to the source as well as files deleted from the source are kept in the backup folder.
Overwrite (differential)	The first backup job runs like a normal backup. As each additional backup job runs, files are added to and deleted from the backup folder. The backup destination folder is always the same size as the backup source folder.

5 Click *Add*.

6 Click *Browse* under "Backup Source Folder Name".

7 Select the shared folder that will be the backup source, then click *OK*.



8 Click *Browse* under "Backup Target Folder Name".

9 Select the backup target and click *OK*.



10 Click *OK*. New backup jobs are now visible.

11 Click *Close*.

Backing Up Your Mac with Time Machine

Time Machine is a backup program included with OS X. To use your LinkStation as a backup destination for Time Machine, configure is as described below.

1 Make sure that AFP is enabled in Advanced Settings. The AFP switch should be in the On position.

2 Choose *Folder Setup*.

3 Choose a shared folder as your backup destination for Time Machine.

4 Click *Edit*.

5 Select *AFP (Mac)* from "LAN Protocol Support" and click *OK*.



6 Click *OK*.

7 Click *Close*.

8 Click *Backup*.



9 Click the icon to the right of "Time Machine".

10 Click *Edit*.

11 Click *Browse*.



12 Select the shared folder that you set in the previous step, then click *OK*.



13 Click *OK*.

14 Click *OK*.

15 Move the Time Machine switch to the

position to enable Time Machine.

16 On the Mac, open *System Preferences*.

17 Click *Time Machine*.

18 Click *Choose Backup Disk*.

Time Machine
Show All
Choose Backup Disk...
Time Machine
Time Machine keeps copies of everything on your Mac, including system files, applications, and settings, as well as your music, pictures, and other important files. Since Time Machine keeps daily backups, you can revisit your Mac as it appeared in the past.
OFF
ON
Show Time Machine status in the menu bar
Click the lock to prevent further changes.

19 Select the LinkStation, then click *Use for Backup*.



20 Enter a username and password with the rights to access the shared folder on the LinkStation, then click *Connect*.



Note: If access restrictions are not configured on the target share, log in with the administrator account. The default username and password for the administrator account are "admin" and "password". If access restrictions are configured, log in with an account with write privileges.

21 Time Machine will count down from 120 seconds and the backup will begin.

Copying from a USB Device

Use Direct Copy to copy from a USB device directly to the LinkStation.

These devices are supported:

- USB mass storage devices
- Card readers (except for card readers that can recognize two or more memory cards)
- Digital cameras and other PTP devices
- USB printers

These devices are not supported:

- USB hubs
- Mice
- Keyboards

Configuring Direct Copy

Configuration from a Smartphone

1 In the mobile mode Settings, tap *USB Device*.

2 Move the Direct Copy switch to the position to enable Direct Copy, then tap *Apply*.



The data from the USB drive will be copied to the target folder. You may change the target folder from the drop-down list if desired.

Configuration from a Computer

1 In Advanced Settings, move the Direct Copy switch to the

position to enable Direct Copy.

To change the Direct Copy target folder, navigate to *Backup - Direct Copy - Edit*, select a new folder, and click *OK*.



Starting Direct Copy

1 Connect the USB device. When it mounts (about 10 seconds), the function LED will light up.

Note: Devices that don't trigger the function LED to light up are not supported.

2 You now have 60 seconds to hold down the function button for 3 seconds. If you do, the function LED will flash as all the files on the USB device are copied to the Direct Copy folder of the LinkStation.

Notes:

- While the function LED is flashing, hold the function button down for 3 seconds to cancel Direct Copy.
- For digital cameras that are not in the USB mass storage class, all files from the digital camera are copied.

3 When the copy operation is finished, the access LED of the USB device will stop flashing. Hold down the function

button for 8 seconds. The function LED will flash as all external drives are dismounted, which will take about 30 seconds. When the dismount is finished, the function LED will stop flashing and glow steadily. You now have 60 seconds to unplug any USB drives safely.

Note: You can start Direct Copy from smartphone Settings even after 60 seconds have passed. Go to Settings from your smartphone and tap *Start Direct Copy*.



Chapter 7 Multimedia

DLNA

DLNA is a set of guidelines for sharing digital media. The LinkStation includes a DLNA server compliant with the DLNA guidelines. Movies, photos, and music saved on the LinkStation can be played back on DLNA-compatible TVs, stereo equipment, game consoles, and other devices on the local network.



Configuration from Smartphone

1 In the mobile mode Settings, tap *DLNA Server*.



2 Enable the shared folder for DLNA and tap *Apply*.



Configuration from Easy Admin

1 Click the ⚙ icon for "DLNA".

2 Move the DLNA switch to the On position to enable DLNA.



3 Move the switch for the folder you'll use for DLNA media to the On position as well.



4 Click *Apply*.

Configuration from Advanced Settings

1 Navigate to *File Sharing - Folder Setup*.

2 Select the folder that you want to share with media players and other DLNA-compatible devices.

3 Click *Edit*.

4 Enable "DLNA" under "LAN Protocol Support", then click *OK*.



5 Click *Services*.



6 Move the DLNA Server switch to the

position to enable DLNA.

7 Click the icon to the right of "DLNA Server".

8 Click *Edit*.

9 Select an interval for DLNA server database updates and click *OK*.



Play Files

To play back content from a DLNA-compatible device:

1. Connect the DLNA-compatible device to the same network as the LinkStation and turn it on.
2. Select the LinkStation in the software of the DLNA-compatible device.
3. Select the content to be played back.

Connected DLNA-compatible Devices

Follow the procedure below to view the DLNA-compatible devices connected to your LinkStation.

1. In Advanced Settings, click *Services*.



2. Click the icon to the right of "DLNA Server".
3. Click *DLNA Client Access Permissions*.
4. A list of the MAC addresses, IP addresses, and device names of the DLNA-compatible devices connected to the same network as the LinkStation is displayed. If your device is not listed, click *Refresh Database*.



Streaming to DLNA-compatible Devices

When new movies, photos, and music files are added to the LinkStation's DLNA folder, the database must be updated before the new files can be streamed. By default, the database is updated when the files are stored in the LinkStation. You can change this interval or update the database manually.

1 In Advanced Settings, click *Services*.



2 Click the icon to the right of "DLNA Server", then click *Edit*.

3 You may change the update interval, or select *Refresh Database* to update the database immediately.



Disabling Playback from Specific Devices

You may block specific DLNA devices from playing back media content.

1 In Advanced Settings, click *Services*.



2 Click the icon to the right of "DLNA Server".

3 Click *DLNA Client Access Permissions*.

4 Uncheck the devices you do not want to allow to play media and click *OK*.



Supported File Types

The LinkStation supports DLNA streaming of files with the extensions below.

Type	File Extensions
Video Files	mpe, mpeg, mpeg2, mpg, m2p, tts, m2ts, m2t, mts, m1v, m4v, mp4, mov, wmv, avi, divx, xvid, asf, dvr-ms, vob, 3gp, vdr, spts, tp, ts
Picture Files	jpg, jpeg, png, bmp, gif, tif, tiff, yuv
Music Files	mp3, wma, wav, lpcm, pcm, ogg, m4a, mp4, 3gp, flac, m3u, mpa, aac, apl, ac3, aif, aiff, mp2, mp1

iTunes Server

If the iTunes server is enabled, computers on your network with iTunes can play music files stored on the LinkStation and transfer them to iPod, iPhone, and iPad devices. The iTunes server supports playback from up to five computers.

1 In Advanced Settings, click *Services*.



2 Click the icon to the right of "iTunes Server".

3 Click *Edit*.

4 Click *Browse*.

5 Select the shared folder that you want to make available to iTunes, then click *OK*.



6 Click *OK*.

7 Make sure that the iTunes server is enabled. The iTunes server switch should be in the On position.

BitTorrent

BitTorrent is a protocol for distributing large amounts of data efficiently. The information in this chapter is for users who are familiar with BitTorrent.

Note: Use compatibility mode to use "Download Manager" with Windows 8 and Windows 8.1.

Configuring BitTorrent

Configuration from Easy Admin

1 Click *BitTorrent*.



2 Move the BitTorrent switch to the On position to enable BitTorrent.



3 Select the shared folder to save files downloaded via BitTorrent from the drop-down list, then click *Apply*.

Configuration from Advanced Settings

1 Click *Applications*.



2 Click the icon to the right of "BitTorrent".

3 Click *Edit*.

4 Click *Browse*.



5 Select the shared folder where the downloaded file will be saved, then click *OK*.



6 Enter the port number, then click *OK*.

7 Move the BitTorrent switch to the On position to enable BitTorrent.

Opening Download Manager

Note: The default username is "admin" and the default password is blank (no password).

Opening from Easy Admin

1 Click *BitTorrent*.



2 The download manager will open.



Opening from Advanced Settings

1 Click *Applications*.



2 Click the icon to the right of "BitTorrent".

3 Click *Open Download Manager*.



4 The download manager will open.



Downloading Files

1 Open the download manager.

2 Click the icon.

3 Enter the URL at "Or enter a URL:" and click *Upload*. The downloaded file will be saved in the folder that is specified in the "Destination folder" field.



Note: Check "Start when added" to start downloading immediately after clicking *Upload*.

4 The download will start.

Note: To cancel downloading, click and *Remote*. Click to pause the download. Click or to resume.

Connecting a Printer

You can connect a printer to the USB port on the LinkStation.

Notes:

- Only one USB printer can be connected to the LinkStation.
- Bidirectional communication is not supported i.e., remaining ink quantities and other printer status information is not supported.

- Don't disable the SMB protocol while the printer server is enabled. If you do, you will need to enable SMB again and reconfigure the print server from scratch.

Setting up a Printer from a Smartphone

1 Connect a printer to the LinkStation's USB port, then turn the printer on.

2 In the mobile mode Settings on a smartphone, tap *USB Device*.

3 Move the print server switch to the position to enable the print server.

4 Tap *Apply*, then *OK*.

Settings up a Printer with Windows 8.1, Windows 8, Windows 7, or Windows Vista

1 Connect a printer to the LinkStation's USB port, then turn the printer on.

2 In Advanced Settings, click *Services*.



3 Move the print server switch to the position to enable the print server.

4 Refer to the manual supplied with the printer and install the printer drivers.

5 Launch NAS Navigator2. Double-click your LinkStation's icon.

6 Double-click the icon of the connected printer (shared name is displayed).



7 Click *OK*.


Connect to Printer
The server for the printer does not have the correct printer driver installed. If you want to search for the proper driver, click OK. Otherwise, click Cancel and contact your network administrator or original equipment manufacturer for the correct printer driver.
OK
Cancel

8 Select your printer, then click *OK*.


Add Printer Wizard
Select the manufacturer and model of your printer. If your printer came with an installation disk, click Have Disk. If your printer is not listed, consult your printer documentation for a compatible printer.
Manufacturer
Apollo
Brother
Canon
Citizen
Printers
Apollo P-1200
Apollo P2100/P2300U
Apollo P2200
This driver is digitally signed.
Tell me why driver signing is important
Have Disk...
OK
Cancel

9 Register the printer.

Setting Up a Printer with Windows XP

1 Connect a printer to the LinkStation's USB port, then turn the printer on.

2 In Advanced Settings, click *Services*.



3 Move the print server switch to the

position to enable the print server.

4 Refer to the manual supplied with the printer.

5 Launch NAS Navigator2. Double-click your LinkStation's icon.

6 Double-click your printer icon.

7 When "The server for the printer does not have the correct printer driver installed. If you want to search for the proper driver, click *OK*." displays, click *OK*.

8 Select the driver connected to the LinkStation, then click *OK*.


Add Printer Wizard
Select the manufacturer and model of your printer. If your printer came with an installation disk, click Have Disk. If your printer is not listed, consult your printer documentation for a compatible printer.
Manufacturer
Generic
Gestetner
HP
IBM
Infotec
Iwatsu
Printers
HP LaserJet Plus
HP LaserJet Series II
HP Mopier 240 PCL
HP Mopier 240 PS
HP Mopier 320 PCL
This driver is digitally signed.
Tell me why driver signing is important
Have Disk...
OK
Cancel

9 Register the printer.

Chapter 8 Advanced Features

Email Notification

Your LinkStation can send you email reports daily, or when settings are changed or an error occurs. Notification emails may be triggered by any of the following events:

- Hard drive status at scheduled time
- Hard drive read error
- Backup job completed

1 In Advanced Settings, click *Management*.



2 Move the email notification switch to the

position to enable email notification.

3 Click to the right of "Email Notification".

4 Click *Edit*.

5 Enter your mail server settings and choose what events will trigger notification. Click *OK* to send a test email.



Sleep Mode

To save energy, you can specify times to put the LinkStation into sleep (standby) mode, where the hard drive and LEDs are turned off.

1 In Advanced Settings, click *Management*.



2 Click to the right of "Sleep Timer".



3 Click *Edit*.

4 Specify the timer interval, wake-up time, and time to go into sleep mode, then click *OK*.



Notes:

- Up to three timers can be set.
- The time to enter sleep mode can be set from 0:00 am to 3:45 of the next day.
  The time to wake from sleep mode can be set from 0:00 to 23:45.
  If the time to enter sleep mode is after 24:00, the wake-up time setting may be from 4:00 am to 23:45.
- The time to enter sleep mode should not be set at the same time as or before the wake-up time.
- If a backup task is scheduled during a disk check, disk format, backup job or within 5 minutes of the current time, the LinkStation will not change to standby mode when the time to enter sleep mode is reached.
- If the scheduled times in the timer overlap, operation is performed using the widest time interval.
- Examples of multiple timer settings are shown below.
  Example 1:
  If running at a current time of 10:00 Wednesday
  Timer 1: Daily 12:00-24:00
  Timer 2: Not used
  Timer 3: Not used
  No operation is performed at 12:00 and the unit goes into sleep mode at 24:00.

Example 2:
When running at a current time of 10:00 Wednesday
Timer 1: Daily 9:00-18:00
Timer 2: Wednesday 10:00-20:00
Timer 3: Not used
On days other than Wednesday, normal operation begins at 9:00 and the unit goes into sleep mode at 18:00. On Wednesday, the unit goes into sleep mode at 20:00.
Example 3:
If running at the current time of 10:00 Wednesday
Timer 1: Daily 9:00-18:00
Timer 2: Wednesday 10:00-3:00 the next day
Timer 3: Not used
On days other than Wednesday, normal operation begins at 9:00 and the unit goes into sleep mode at 18:00. On Wednesday, normal operation begins at 9:00 and the unit goes into sleep mode at 1:00 the next day.
Example 4:
When running at a current time of 10:00 Wednesday
Timer 1: Daily 9:00-18:00
Timer 2: Wednesday 7:30-22:00
Timer 3: Not used
On days other than Wednesday, normal operation begins at 9:00 and the unit goes into sleep mode at 18:00. On Wednesday, normal operation begins at 7:30 and the unit goes into sleep mode at 22:00.

- To turn on the LinkStation before the wake-up time when it is in sleep mode, press the function button.

Encrypting Data Transmission

Encrypting Settings Data

All communication to Settings can use SSL encryption if you access Settings through https://.

Encrypting FTP Transfer Data

You can encrypt passwords and files using SSL/TLS for secure FTP communication. First, in the shared folders settings, select *FTP* under *LAN Protocol Support* in Settings. Enable SSL security in the setup screen for your FTP client. The procedure depends on the FTP client software.

SSL Encryption

SSL is a cryptographic protocol for communication security and data confidentiality over the Internet. To use SSL, you will need a certificate and a key. These are available from web hosting services and many private privacy providers.

Configuring SSL

To enter or update a server certificate and private key for SSL, following this procedure.

1 Navigate to *Management* - *SSL*.

2 Enter or browse to the locations of the key and certificate, then click *Import*.

Restoring Factory Defaults

To initialize the LinkStation to its factory default settings, follow this procedure.

Initializing from Settings

1 In Advanced Settings, click *Management*.



2 Click the icon to the right of "Restore/Erase".

3 Click *Initialize LinkStation*.


Restore/Erase
This initializes the LinkStation's settings. All settings are restored to their factory defaults.
Saved data is not erased.
Initialize LinkStation

4 The "Confirm Operation" screen will open. Enter the displayed number, then click *OK*.

5 The LinkStation will be restored to its factory default settings.

Initializing with the Function Button

You can also initialize the settings with the function button.

1 Turn off the LinkStation.

2 Turn the LinkStation on with holding down the function button. The function LED will flash white.

3 Press the function button again while the LED is flashing.

4 Initialization will take 5 to 10 minutes. Do not power down the LinkStation while it is initializing and showing an "I23: System is being initialized..." information code in NAS Navigator2 and with the power LED. When initialization is finished, the LinkStation will automatically reboot.

Notes:

- The following settings will be initialized: admin username, admin password, IP address, and Ethernet frame size.
- To disable initializing usrname and password, navigate to *Management* - *Restore/Erase* - *Edit* and change "Restore factory default settings" to "Keep current settings". Be careful with this option! If this is selected and you lose your admin password, you will not be able to reset it.

Online Update

If a new firmware is available, a message is displayed when the LinkStation boots. You can update the firmware as

follows:

1 In Advanced Settings, click *Management*.



2 Choose *Update*.

3 Click *Install Update*.

Notes:

- Settings is not available while the firmware is updating. Don't try to access Settings from another computer until the update is complete.
- You can disable update notifications in *Management - Update*.
- To clear an update notification, press the function button.

Name, Date, Time, and Language

Configure the LinkStation's hostname, date, time, and language as follows.

1 In Advanced Settings, click *Management*.



2 Open *Name/Time/Language*.

3 Click *Edit*.

4 Click the *Name* tab and configure the LinkStation's name and description.



5 Click the *Time* tab. Enable NTP server and check "Use Local Date/Time" to use your computer's time settings for the LinkStation.



By default, the LinkStation adjusts its clock automatically by using a default NTP server. This NTP server belongs to Internet Multi Feed Inc. For more information, visit http://www.jst.mfeed.ad.jp.

To use a different NTP server, navigate to *Management - Name/Time/Language*. Click *Time*, then *Edit*. Uncheck "Use Default NTP Server" and enter a new NTP IP address. Click *OK*.

If NTP is not used, enter the time and date manually. Click *Use Local Date/Time* to import the time and date from your computer.

If an NTP server is specified by name instead of IP address, make sure that a DNS server is configured for the LinkStation.

Note: The internal clocks of the LinkStation and other devices on your network may run at slightly different speeds. Over a long period of time your network devices may show somewhat different times, which can cause network problems. If clocks on your network vary by more than 5 minutes it may cause unexpected behavior. For best results, keep all clocks on the network set to the same time by adjusting them regularly, or use an NTP server to correct them all automatically.

6 Click the *Language* tab. Select the language to be used in the Windows client, then click *OK*.



Note: This tab changes the language used by the LinkStation for email notification, DLNA, and other functions. To change the language displayed in Settings, go to Advanced Settings or Easy Admin and click *Language* in the menu bar. Choose your desired language from the drop-down menu.

Jumbo Frames

If your other network devices support it, you may be able to increase network performance with jumbo frames.

1 In Advanced Settings, click *Network*.



2 Click to the right of "IP Address".

3 Select the LAN port.

4 Click *Edit*.

5 Select your desired Ethernet frame size and click *OK*.





Changing the IP Address

Normally, the LinkStation's IP address is set automatically from a DHCP server on your network. If you prefer, you can set it manually. An easy way to do this is to change it from NAS Navigator2 running on a computer connected to the same router (subnet) as the LinkStation. The procedure to change the IP address in Settings is below.

1 In Advanced Settings, click *Network*.



2 Click to the right of "IP Address".

3 Select the LAN port.

4 Click *Edit*.

5 Disable "DHCP", enter the desired network address settings, and click *OK*.

Chapter 9 Utilities

NAS Navigator2 for Windows

NAS Navigator2 is a utility program that makes it easy to display Settings, change the LinkStation's IP address, or check its hard drive. If you installed the LinkStation with the LinkNavigator CD, NAS Navigator2 was installed automatically.

NAS Navigator2 will run in the system tray when the computer is on.

To launch NAS Navigator2, double-click the icon.



Click your LinkStation's icon to open a share on the LinkStation and display:

- Total capacity
- Capacity in use
- IP address
- Workgroup
- Subnet mask
- Default gateway
- MAC address
- Firmware version

Name		Description
Menu	Map Share*	Assigns the LinkStation's shared folder as a network drive.
	Disconnect Share*	Unmaps the network drive.
	Map All Remote Shares to Drive Letters	Assigns all the LinkStation's shared folders as network drives.
	Create Desktop Shortcut*	Creates a shortcut to the LinkStation's shared folder (share).
	Launch NAS Navigator2 on Startup	Launches NAS Navigator2 in the system tray when Windows boots.
	Display Errors	If an error occurs, an error message will pop up from the NAS Navigator2 icon in the system tray.
	Properties*	Opens the selected LinkStation's properties page.
	Close	Closes NAS Navigator2.
	View	Icons: Displays icons. Details: Displays hostname, product name, workgroup, IP address, subnet mask, and default gateway.
	Sort by	If you have multiple LinkStations and TeraStations on the network, you may choose to display them in order of hostname, product name, workgroup, IP address, subnet mask, or default gateway.
Browse*		Opens the LinkStation's shared folder.
Refresh		Searches for NAS devices on the network again.
Displays when you right-click a device's icon.	Browse Shares	Opens the LinkStation's shared folder.
	Settings	Opens Settings for the selected LinkStation.
	Properties	Opens the LinkStation's properties page.
	Map Share	Assigns the LinkStation's shared folder as a network drive.
	Disconnect Share	Unmaps the network drive.
	Create Shortcut	Creates a shortcut icon to the shared folder "share" on the desktop.

*Click on the LinkStation's icon to display these options.

When NAS Navigator2 is minimized, right-click on the NAS Navigator2 icon in the system tray for the following options.



Name		Description
NAS Name	Browse Shares	Opens the LinkStation's share folder.
	Settings	Opens Settings for the selected LinkStation.
	Properties	Opens the LinkStation's properties page.
	Map Share	Assigns the LinkStation's shared folder as a network drive.
	Disconnect Share	Unmaps the network drive.
	Create Shortcut	Creates a shortcut icon to the LinkStation's shared folder (share) on the desktop.
Refresh		Refreshes list of NAS devices.
Browse Shares		Displays NAS Navigator2 window.

Exit	Exits NAS Navigator2.

The following tasks may be performed from the LinkStation's properties page.



Name	Description
Configuration	Click *Settings* to open the configuration interface.
IP Address	Check *Use DHCP* to assign an IP address from the DHCP server automatically. If there is no DHCP server in the network, you cannot use this function. Check *Renew IP address* to obtain an IP address from the DHCP server. You can manually enter an IP address, subnet mask, and default gateway.

Mount as Network Drive

You can easily map a shared folder as a network drive using NAS Navigator2.

1 Double-click the icon on the desktop. NAS Navigator 2 will start.

2 Right-click on the LinkStation's icon and choose *Map Share*.



Note: The following shared folders can be mounted as network drives from NAS Navigator2: share, share2, share3,

share4, usbdisk1, usbdisk2, usbdisk3, usbdisk4, usbdisk5

3 An icon for the mapped share will appear in Computer or My Computer. You can use this network drive just like any other hard drive.

Changing the IP Address

1 Click the icon on the desktop. NAS Navigator2 will start.

2 Right-click on your LinkStation's icon and choose *Properites - IP Address.*.

3 Uncheck "Use DHCP", enter the IP address and subnet mask, and click *OK*.



NAS Navigator2 for Mac OS

NAS Navigator2 is a utility that makes it easy to display Settings, change the LinkStation's IP address, or check its hard drive. If you installed the LinkStation with the LinkNavigator CD, NAS Navigator2 was installed automatically.

To launch it, click the icon in the Dock.



Click your LinkStation's icon to open a share on the LinkStation and display:

- Total capacity
- Capacity in use
- IP address
- Workgroup
- Subnet mask
- Default gateway
- MAC address
- Firmware version

Name		Description
Open		Opens the default shared folder for a selected LinkStation.
Refresh		Searches for NAS devices on the network again.
Settings		Opens Settings for the selected LinkStation.
Configure		Opens a window that lets you configure the NAS's IP address or open Settings.
Label Color		Selects the color of the name displayed below the icon.
View Options		Lets you choose icon size, position, and view mode.
Auto Power Mode		Auto power mode can turn supported TeraStations and LinkStations on the network on and off automatically.
To display these options, hold down the control key and select your LinkStation's icon.	Open Folder	Opens the LinkStation's shared folder.
	Settings	Opens Settings for the selected LinkStation.
	Configure	Opens a window that lets you configure the NAS's IP address or open Settings.
	Label Color	Selects the color of the name displayed below the icon.

Mount as Network Drive

You can map a shared folder as a network drive from NAS Navigator2.

1 Click the icon in the Dock. NAS Navigator2 will launch.

2 Double-click the LinkStation icon or click the LinkStation icon while holding down the control key, then select *Open Folder*. Enter a username and password with the rights to access the shared folder.



3 Select the shared folder to mount and click *OK*.

4 The shared folder is now mounted as a network drive.

Changing the IP Address

1 Click the icon in the Dock. NAS Navigator2 will start.

2 Hold down the control key, select your LinkStation, and choose *Configure... - IP Address*.

3 Uncheck "Use DHCP", enter the IP address and subnet mask, and click *OK*.


NASNavigator2
LS210D006
LS210D Series
Configuration
IP Address
Use DHCP
Renew IP address
IP Address:
Subnet Mask:
0
0
0
0
Default Gateway:
192
168
10
1
Administrator Password
Cancel
Apply

Chapter 10 Appendix

When the Power LED Blinks

White

The power LED will blink white during bootup or shutdown.

Red

If there is an error, the power LED will blink red. The pattern of the blink gives the error code. You can also see any errors in NAS Navigator2.

Place of Error Code	Status
10s Place of Error Code	The LED flashes for 1.0 second every 0.3 seconds. This gives the tens place of the error code.
1s Place of Error Code	The LED flashes for 0.5 seconds every 0.3 seconds. This gives the ones place of the error code.

Error Code	Description	Corrective Action
E07	The firmware is corrupted.	Contact Buffalo technical support for assistance.
E11	An error occurred in the fan speed.	Check the fan. Use compressed air or tweezers to remove any dust or foreign objects. Confirm that the fan is spinning normally. If it is not, contact Buffalo technical support for assistance.
E12	A rise in the system temperature may have exceeded the allowable safety value.	Do not place objects in the area around the LinkStation. Also, move the LinkStation to a cool location.
E13	An error occurred in the RAID array. The LinkStation is in degraded mode.	Replace the defective drive. Reboot the LinkStation and rebuild the RAID array.
E14	RAID array X cannot be mounted.	Run the RAID array disk check in Settings.
E15	The bad sectors have reached a dangerous level.	Replace the defective drive.
E16	Unable to find hard drive X.	Hard drive X may be disconnected or may have failed. Shut down the LinkStation and reinstall the hard drive.
E22	Mounting of hard drive X failed.	Format the hard drive. After formatting, if the error still appears after rebooting, replace the hard drive. If the error is displayed again, contact Buffalo technical support for assistance.

E23	An error occurred, so the hard drive was removed from the RAID array.	Replace the faulty drive.
E30	A hard drive error occurred.	Replace the faulty drive.

Amber

If there is a status message, the power LED will blink amber. The pattern of the blink gives the information code. You can also see any status messages in NAS Navigator2.

Place	Status
10s Place	The LED flashes for 1.0 seconds every 0.3 seconds. This gives the tens place of the information code.
1s Place	The LED flashes for 0.5 seconds every 0.3 seconds. This gives the ones place of the information code.

Information Code	Description	Corrective Action
I10	A rise in system temperature may have exceeded the allowable safety value.	Move the LinkStation to a cool location. Do not place objects in the area around the LinkStation.
I11	The bad sectors in hard drive X may have reached a dangerous level.	Replace hard drive X.
I12	Operating in degraded mode.	-
I13	Formatting RAID array X.	-
I14	Checking RAID array X.	-
I15	Examining the error status of RAID array X. **Note:** Transfer speeds are slower during the examination process.	-
I16	Creating RAID array X.	-
I17	Resynchronizing RAID array X. **Note:** Transfer speeds are slower during resynchronization.	-
I18	Rebuilding RAID array X. **Note:** Transfer speeds are slower during the rebuilding process.	-
I19	Writing 0s to RAID array X, erasing all data.	-
I20	Formatting hard drive X.	-
I21	Checking hard drive X.	-
I22	Erasing the data for hard drive X.	-
I23	System is being initialized.	-
I25	Updating the LinkStation firmware.	-
I26	Initializing all settings.	Don't turn off the LinkStation.
I27	Checking USB hard drive.	-
I28	Formatting USB hard drive.	Don't turn off the LinkStation.
I46	Data migration or conversion (RAID migration) is in progress.	Don't turn off the LinkStation.
I47	Data migration or conversion (RAID migration) is in progress.	Don't turn off the LinkStation.
I52	A new firmware version has been released.	Update the firmware.

I54	A backup task has failed.	Make sure that the backup task is configured correctly. Make sure that the NAS is on and not in standby mode. If the backup task still fails, check the status of the network and backup source and destination.

Amber (Not Blinking)

When the power LED glows a steady amber, a new firmware version is available. Update the firmware to the newest version.

Default Settings

Administrator's Name	admin
Password	password
Shared Folders	"share" (for both Windows and Mac computers). The recycle bin is enabled on "share" by default.
DHCP Client	Normally, the LinkStation will get its IP address automatically from a DHCP server on the network. If no DHCP server is available, then an IP address will be assigned as follows: IP address: 169.254.xxx.xxx (xxx is assigned randomly when booting the LinkStation.) Subnet mask: 255.255.0.0
Registered Groups	"hdusers", "admin", and "guest" These groups cannot be deleted or modified.
Microsoft Network Group Setting	WORKGROUP
Ethernet Frame Size	1518 bytes (Including 14 bytes of header and 4 bytes of FCS)
SMB2	Disabled
AFP	Enabled
FTP	Disabled
NTP	Enabled
Print Server	Disabled
WebAccess	Disabled
Time Machine	Disabled
DLNA Server	Disabled
iTunes Server	Enabled
BitTorrent	Disabled
Function Button Intialization	Restore factory default settings
Update Notification	Enabled

Specifications

Check www.buffalotech.com for the latest product information and specifications.

LAN Port	Interface	IEEE 802.3ab (1000BASE-T) IEEE 802.3u (100BASE-TX) IEEE 802.3 (10BASE-T)
	Transfer Speed	1000 Mbps Full duplex (auto-negotiation) 100 Mbps Full duplex/Half duplex (auto-negotiation) 10 Mbps Full duplex/Half duplex (auto-negotiation)
	Number of Ports	1 Port (supports Auto-MDIX)
	Connector Type	RJ-45 8-pin
	Protocol	TCP/IP
	Access Method	CSMA/CD
	File Sharing	SMB/CIFS, AFP, FTP
	Management	HTTP/HTTPS
	Jumbo Frames	1518, 4102, 7422, and 9216 byte modes are supported (Including 14 bytes of header and 4 bytes of FCS)
USB Port	USB 2.0 Port (Series A) x 1 **Note:** Compatible USB devices include printers and Buffalo USB hard drives.	
Power Supply	AC 100 - 240 V, 50/60 Hz	
Power Consumption	1-2 TB models: max ~18 W 3+ TB models: max ~24 W	
Dimensions (WxHxD) / Weight	45 x 128 x 205 mm (excluding protruding parts)/ ~1.1 kg (2.4 lb.)	
Operating Environment	Temperature: 5 - 35°C; 41 - 95°F Environment humidity: 20 - 80% (no condensation)	
Compatibility	iPhone, iPad, iPad mini, iPod touch* Android smartphones and tablets** Windows 8.1, Windows 8, Windows RT 8.1, Windows RT, and Windows Phone Windows and Mac computers with Ethernet interface *iOS 5 or later **Android 2.3 or later **Note:** The LinkStation requires an Ethernet connection with your computer for operation. It cannot be connected via USB.	
Supported OS	Windows 8.1*, Windows 8*, Windows 7*, Windows Vista*, Windows XP, Windows XP Media Center Edition (2004 and 2005), Windows Server 2012 R2, Windows Server 2012, Windows Server 2008 R2, Windows Server 2008 OS X 10. 9, 10.8, 10.7, 10.6 *32-bit and 64-bit	

Compliance Information

FCC Statement

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) This device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of

the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Environmental Information

- The equipment that you have purchased required the extraction and use of natural resources for its production.
- The equipment may contain hazardous substances that could impact health and the environment.
- In order to avoid the dissemination of those substances in our environment and to diminish the load on natural resources, we encourage you to use the appropriate take-back systems.
- The take-back systems will reuse or recycle most of the materials of your end of life equipment appropriately.
- The crossed-out wheeled bin symbol invites you to use those systems.
- If you need more information on the collection, reuse and recycling systems, please contact your local or regional waste administration.

Models

LS210D0101, LS210D0201, LS210D0301, LS210D0401